

PCT


WORLD INTELLECTUAL PROPERTY ORGANIZATION  
International Bureau



INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

<p>(51) International Patent Classification<sup>6</sup> : <b>G11C 19/28, H01J 31/49, G06K 7/00, 9/00</b></p>	<p><b>A1</b></p>	<p>(11) International Publication Number: <b>WO 98/56006</b></p> <p>(43) International Publication Date: 10 December 1998 (10.12.98)</p>
<p>(21) International Application Number: PCT/US98/11106</p> <p>(22) International Filing Date: 1 June 1998 (01.06.98)</p> <p>(30) Priority Data: 08/867,652 2 June 1997 (02.06.97) US</p> <p>(71) Applicant: SARNOFF CORPORATION [US/US]; 201 Washington Road, CN 5300, Princeton, NJ 08543-5300 (US).</p> <p>(72) Inventors: MCCAFFREY, Nathaniel, J.; 412 Lambertville Hopewell Road, Hopewell, NJ 08530 (US). SAUER, Donald, J.; 8 Twain Drive, Allentown, NJ 08501 (US). LEVINE, Peter, A.; 38 Dunbar Drive, R.R.4, Trenton, NJ 08691 (US). PANTUSO, Francis, P.; 30 Spring Garden Road, Robbinsville, NJ 08691 (US).</p> <p>(74) Agents: BURKE, William, J. et al.; Sarnoff Corporation, 201 Washington Road, CN 5300, Princeton, NJ 08543-5300 (US).</p>		<p>(81) Designated States: AU, BR, CN, JP, KR, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).</p> <p><b>Published</b> <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i></p>

(54) Title: EXTENDED DYNAMIC RANGE IMAGING SYSTEM AND METHOD



(57) Abstract

In one embodiment, an imager (201) has an array of photodetectors, each of which accumulates charge during an integration period as a result of light detected during the integration period, the array having a charge capacity which increases during the integration period. A charge capacity controller (202) coupled to the imager (201) adjusts how the imager (201) increases the charge capacity of the array based upon the brightness distribution detected by the imager (201) during at least one previous integration period.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

## **EXTENDED DYNAMIC RANGE IMAGING SYSTEM AND METHOD**

### **BACKGROUND OF THE INVENTION**

#### **Field of the Invention**

10       The present invention relates to imaging systems and, in particular, to imaging systems which increase photodetector charge capacity towards the end of the integration period to extend the dynamic range of the imaging system.

#### **Description of the Related Art**

15       Various types of imagers or image sensors are in use today, including charge-coupled device (CCD) image sensors and complementary metal-oxide semiconductor CMOS image sensors. These devices are typically incorporated into CCD and CMOS imaging systems, respectively. Such systems comprise an array of pixels, each of which contains a light-sensitive sensor element such as a CCD or, in CMOS image sensors, a virtual gate buried n-channel photodetector, a N+ to p-substrate photodiode, or a photogate detector. Such light-sensitive  
20       sensor elements will be referred to herein, generally, as photodetectors.

      In such devices, the photodetector accumulates charge and hence voltage during the optical integration period in accordance with the light intensity reaching the relevant sensing area of the photodetector. As charge accumulates, the photodetector begins to fill. The charge stored in a photodetector is sometimes said to be stored in the "charge well" of CCD-type  
25       photodetectors. If the photodetector becomes full of charge, then excess charge is shunted off, in part to prevent blooming. Blooming is a phenomenon in which excess charge beyond pixel saturation spills over into adjacent pixels, causing blurring and related image artifacts. However, if the photodetector becomes full before the end of the integration period and any additional photons strike the photodetector, then no additional charge can be accumulated. Thus, for  
30       example, if very bright light is applied to a photodetector, this can cause the photodetector to be full before the end of the integration period and thus to saturate and lose information.

      U.S. Patent No. 3,953,733, issued April 27, 1976 to Levine ("Levine"), the entirety of which is incorporated herein by reference, teaches a method of operating CCD imagers to avoid this problem. The voltage applied to the electrodes of a CCD cause a heavily depleted region to

form beneath the electrode, which forms "potential wells" or charge wells of a given maximum charge capacity. A greater electrode voltage causes a correspondingly greater charge capacity well to form. The voltage that controls the maximum charge capacity of a photodetector, such as the CCD electrode voltage, will be referred to herein as the charge capacity control voltage, and  
5 the maximum charge that can be accumulated in a photodetector will be referred to herein as the photodetector's charge capacity. The charge capacity control voltage is also sometimes referred to as the blooming barrier voltage, since it acts as a blooming drain to remove charge from the pixel photodiode to avoid charge spilling into adjacent pixels during optical overload.

Typically, the charge capacity control voltage applied is constant throughout the  
10 integration period, so that a given charge capacity exists throughout the integration period for each pixel of the imager array. In Levine, the charge capacity control voltage is varied during the integration period, so as to increase the optical dynamic range of the CCD imager. For example, in one embodiment, Levine teaches increasing the charge capacity control voltage (and hence the charge capacity) in non-linear fashion, by increasing the charge capacity control voltage in  
15 discrete steps towards the end of the integration period. Levine also teaches other methods of increasing the charge capacity control voltage and charge capacity towards the end of the integration period to extend the dynamic range of the imaging system, such as using enough multiple discrete steps to implement a continuously increasing charge capacity control voltage; or using linearly increasing charge capacity control voltage waveforms and increasing the slope or  
20 slopes of such waveforms.

However, although this method may be used to extend the dynamic range of a given imager, it is possible that the extended dynamic range may not be utilized for given frames. For example, a given scene may be relatively dark, thus wasting dynamic range at the expense of loss of contrast ratio and scene information content. This may be the case with, for example, imaging  
25 systems used for surveillance purposes.

### **SUMMARY**

A imaging system and method. In an embodiment, an imager has an array of photodetectors, each of which accumulates charge during an integration period as a result of light detected during said integration period, said array having a charge capacity which increases  
5 during the integration period. A charge capacity controller coupled to said imager adjusts how the imager increases the charge capacity of the array based upon the brightness distribution detected by said imager during at least one previous integration period.

### **BRIEF DESCRIPTION OF THE DRAWINGS**

These and other features, aspects, and advantages of the present invention will become  
10 more fully apparent from the following description, appended claims, and accompanying drawings in which:

Figs. 1A-C are diagrams of waveforms illustrating a method for extending the dynamic range of an imager, in accordance with an embodiment of the present invention;

Fig. 2 is a block diagram of a video processing system for dynamically determining the  
15 charge capacity control voltage function used to extend the dynamic range of the system, in accordance with an embodiment of the present invention; and

Fig. 3 shows an exemplary histogram to illustrate the method of operation of the video processing system of Fig. 2.

### DESCRIPTION OF THE PREFERRED EMBODIMENT

Referring now to Figs. 1A-C, there are shown diagrams of waveforms illustrating a method for extending the dynamic range of an imager, in accordance with an embodiment of the present invention. Each of Figs. 1A-C graphs the relative signal charge versus time, for three light levels I1, I2, and I3, where I3 is the most intense light level and I2 is the least intense light level. The relative signal charge is the charge accumulating in the photodiode's charge accumulation region or well in response to light of a given constant intensity. The time  $t$  is shown from  $t = 0$  to  $t = 100\%$  of the integration period, which is typically  $1/30$  or  $1/60$  of a second. The relative signal charge is shown from the range 0.0 to 1.0, where 1.0 indicates the maximum charge capacity of the photodetector, at which point the photodetector saturates.

Fig. 1A illustrates the relative signal charge versus time during the integration period for light levels I1, I2, and I3, where a fixed charge capacity control voltage is applied for the entire integration period, as prior art photodetectors are operated. As illustrated, the higher light levels I2 and I3 both saturate before the integration period is complete, since each causes the charge capacity of the photodetector to be exceeded. Therefore, light levels I2 and I3 both result in the same signal readout from the photodetector, even though they are different. Thus, since light levels I2 and I3 both saturate before the end of the integration period, it is not possible for the produced image to display any image details above these light levels. An array of photodetectors configured to operate at a certain constant charge capacity control voltage during the entire integration period does not have enough dynamic range to allow light levels I1, I2, and I3 to all be measured.

This can be the case for situations such as surveillance purposes, in which the intrascene dynamic range can exceed the dynamic range of the imager, causing saturation or blooming and thus lost information. If the imager lens is "stopped down" by adjusting the mechanical iris, this can effectively lower the slopes of all three light levels I1, I2, and I3, so that none of them saturate, but then the signal to noise ratio in the dark regions of the image is degraded, which again causes loss of information.

It is, therefore, useful to extend the dynamic range of an imaging system, by using a charge capacity control voltage function which increases the charge capacity control voltage in some manner during the integration period, as described above with respect to Levine. In one embodiment, the charge capacity control voltage function is a two-step non-linear voltage

function in which a first charge capacity control voltage V1 is applied to the photodetector during a first portion of the integration period, and a higher charge capacity control voltage V2 is applied to the photodetector after this first portion, until the end of the integration period. In this embodiment, voltage V2 is the maximum charge capacity control voltage, i.e. voltage V2 causes the photodetector to have a maximum charge capacity, and voltage V1 is a fraction of voltage V2, thereby causing the photodetector to have a charge capacity that is a corresponding fraction of the maximum charge capacity.

Thus, charge capacity control voltage V1 is applied from during the first time period, which is a specified fraction of the integration period, and charge capacity control voltage V2 is applied for a second time period equal to the rest of the integration period after the first time period. By increasing the length of the first time period during which voltage V1 is applied, and correspondingly decreasing the second time period during which V2 is applied, a higher overall dynamic range can be obtained.

In the present invention, the charge capacity control voltage function is varied to provide sufficient dynamic range to avoid saturation while maximizing the contrast ratio and information content of the scene. For a two-step non-linear voltage function as described above, the charge capacity control voltage function is varied by varying how the integration period is divided between the first and second time periods. More dynamic range can be obtained by lengthening the first time period and shortening the second time period, at the expense of some loss of contrast information for higher-intensity light levels. The intense light levels that would have saturated if the maximum charge capacity control voltage had been applied during the entire integration period, but that do not saturate because they can add additional charge during the second time period, may be referred to as "compressed," since they will add extra charge to the photodetector for a shorter period of time than lower intensity light levels.

Thus, charge capacity control voltage V1 is applied from time  $t=0$  to time  $t_1$ , and charge capacity control voltage V2 is applied during time  $\Delta t_1$ , where  $\Delta t_1$  is the time period between time  $t_1$  and the end of the integration period. By increasing the time period  $t_1$  during which V1 is applied, and correspondingly decreasing time period  $\Delta t_1$ , during which V2 is applied, a higher overall dynamic range can be obtained. Thus, in one embodiment, for a given first charge capacity control voltage V1 and second charge capacity control voltage V2, the charge capacity control voltage function is varied by varying when time  $t_1$  occurs.

Such a charge capacity control voltage function is illustrated in Figs. 1B and 1C, each having a different time at which voltage V1 changes to V2. Referring now to Fig. 1B, the charge capacity control voltage V1 is set to 80% of the maximum charge capacity control voltage V2. Voltage V1 is increased to voltage V2 at a time t1. Thus, until time t1, there is temporarily a saturation point due to a charge capacity that is only 80% of the maximum charge capacity that will exist when larger voltage V2 is applied after time t1. This allows for the contrast differentiation between light levels I2 and I3 that is not possible using the implementation illustrated in Fig. 1A, in which a constant charge capacity control voltage is used throughout the entire integration period. This is because, although light level I3 still saturates, light level I2 does not, so that light level I3 would produce a greater charge in a photodetector than would light level I2, which can thus be used to differentiate such light levels in an image.

However, because light level I3 does saturate, first period time t1 does not allow light levels of intensities around light level I3 to be differentiated from one another. In Fig. 1C, voltage V1 switches to voltage V2 at a time t2, which is later than time t1. In this implementation, neither light levels I2 nor I3 saturate, thus allowing all light levels up to I3 to be distinguished from one another.

In the present invention, before each frame of video data is captured with the array of photodetectors, the charge capacity control voltage function is optimally adjusted so as to provide sufficient dynamic range to avoid saturation for even the brightest portions of the scene or image captured, while maximizing the contrast ratio and information content of the scene. This is done by using dynamic feedback control from previous images to set the first time period so that the brightest objects in the scene just reach the saturation capacity of the imager, as explained in further detail below. Information from previous frames or images is used, based on the assumption that the brightness distribution of previous frames is a reliable predictor of the brightness distribution of the next frame to be captured.

As will be appreciated, varying the charge capacity control voltage effectively changes the pixel charge capacity, and extends the dynamic range of the pixel by only permitting a fraction of the maximum charge capacity to integrate for most of the frame time and increasing the charge capacity to maximum charge capacity towards the end of the integration time. This allows simultaneous imaging of the detail in both bright and dark regions of a scene. The dynamic adjustment of the charge capacity control voltage effectively creates a non-linear photodetection

response during integration time.

Referring now to Fig. 2, there is shown a block diagram of a video processing system 200 for dynamically determining the charge capacity control voltage function used to extend the dynamic range of the system, in accordance with an embodiment of the present invention.

5 System 200 comprises imager 201, which comprises an array of pixels, each containing a photodetector. System 200 further comprises charge capacity controller 202 coupled to imager 201. Charge capacity controller 202 comprises histogrammer 204, feedback function generator 206, contrast corrector 205, histogram equalization/projection block 207, and MUXs 210 and 211. System 200 also comprises output monitor 220, which is coupled to the output of MUX  
10 211 of charge capacity controller 202. The pixel array of imager 201 may be, for example, a CCD or CMOS array and provides, in one embodiment, 12-bit output pixel values (4096 levels) for each pixel, corresponding to the amount of charge accumulated by each pixel during the integration period. Output monitor 220 requires 8-bit input pixel information. Histogrammer 204 and contrast corrector 205 are coupled or couplable to imager 201 via line 212, and feedback  
15 function generator 206 is coupled or couplable to imager 201 via line 213.

The output pixel information for a frame of captured pixels is fed by imager 201, via bus 212, to histogrammer 204 and contrast corrector 205. Tap line 216 further provides the output pixel information as in input to MUXs 210 and 211. The output of histogrammer 204 is applied, via line 214, to the input of feedback function generator 206 and the input of histogram  
20 equalization/projection block 207. Feedback block provides function information via line 213 to an input of imager 201, and inverse function information to an input of contrast corrector 205. The output of contrast corrector 205 is applied, via MUX 210 and line 217, to histogram equalization/projection block 207 and to MUX 211. The output of histogram equalization/projection block 207 is applied, via line 218 and MUX 211, to the input of monitor  
25 220.

As will be appreciated by those skilled in the art, some or all of the functions of charge capacity controller 202 (i.e., histogrammer 204, feedback function generator 206, contrast corrector 205, histogram equalization/projection block 207, and MUXs 210 and 211), may be implemented in real-time by dedicated digital signal processing hardware, by an application-  
30 specific integrated circuit (ASIC), or by a suitably-programmed general purpose computer processor.

System 200 operates as follows to dynamically adjust the charge capacity control voltage function to optimize the performance of imager 201. First, a scene (frame 0) is captured by imager 201, and applied to histogrammer 204. As will be appreciated by those skilled in the art, a histogrammer sorts the pixels received into "bins" that represent the pixel's gray level, i.e. brightness or intensity. Histogrammer 204 thus provides a histogram containing information representing the global brightness distribution of a given frame. From this distribution, the charge capacity control voltage function can be adjusted to either expand or compress the next image to use the full 4096 levels of gray scale resolution of imager 201.

Referring now to Fig. 3, there is shown an exemplary histogram 300 to illustrate the method of operation of signal processing system 200 of Fig. 2. Exemplary histogram 300 shows the global brightness distribution of pixels of frame 0. From this distribution, brightness or intensity information about frame 0 can be determined by feedback function generator 206, which receives the histogram. Feedback function generator 206 generates function information that sets the first time period for imager 201, for capturing the next frame, so that light at the level of the brightest object in frame 0 will not saturate but will just reach the saturation point of the imager. For light of a given level to just reach the saturation point of the imager means that, at the end of the integration period, light of this level would have caused a photodetector to almost reach full charge capacity. Thus, the function information generated by function generator 206 for a two-step non-linear voltage function is a number indicating the time during the integration period at which the first voltage V1 should change to the second voltage V2.

For example, histogram 300 can be used by feedback function generator 206 to determine what is the intensity or brightness of the brightest part of the image that is considered to be an object (cluster of pixels). Such an analysis can be made, rather than simply using the intensity level of the brightest pixel in the frame, so as to avoid making decision based on defective (always white) pixels or only a few bright pixels. Thus, for example, a decision is made by feedback function generator 206 as to what charge capacity control voltage function to use for the next frame, based on the intensity level or gray scale of the 100 brightest pixels. Thus, for example, if the brightest object (not merely a few isolated pixels) of frame 0 has an intensity of approximately I2, then feedback function generator 206 generates function information that sets the first time period to slightly less than t1, as illustrated in Fig. 1B. If, however, the brightest object of frame 0 has an intensity of approximately I3, then feedback function generator 206 generates function information that sets the first time period to approximately t2, as illustrated in

Fig. 1C.

Thus, by using the dynamic adjustment of the charge capacity control voltage function of the present invention, the next frame to be captured is effectively "compressed" into the working dynamic range of the imager, but is compressed to the minimum extent necessary so as to maximize contrast ratio and scene information content.

In one embodiment, imager 201 controls the charge capacity control voltage during the integration period in accordance with the function information provided by function generator 206. In an alternative embodiment, function generator 206 provides the charge capacity control voltage directly to imager 201 via line 213 during the integration period in accordance with the function generated. In another alternative embodiment, feedback function generator 206 generates function information to ensure only that light at the level of the brightest object in frame 0 does not saturate the imager, but does not ensure that light at this level would almost or just saturate the imager.

System 200 provides further signal processing, as necessary, for the captured video frames. First, since dynamic adjustment of the charge capacity control voltage effectively creates a non-linear photodetection response during integration time, the inverse function of this function is generated by feedback function generator 206 and applied to contrast corrector 205. This allows the non-linear manner in which charge is accumulated to be appropriately mapped to the corresponding light intensity level that caused the charge indicated by the pixel. This helps to maintain true color and contrast representation, which is necessary for color imaging where the pixel color is represented by multiple imaging sensor elements. As will be appreciated, contrast correction is important when several sensor elements are combined to make a color pixel. If one sensor element containing one color component (e.g. red) contains low luminance, it will be uncompressed while another element (e.g. blue) is very bright and is compressed, with no correction for this lopsided compression, the color detected will not be a true representation of the scene. By performing the inverse function on each pixel, the red pixel in this case would remain unchanged while the blue pixel would be decompressed to restore the contrast between the luminances in the sensor elements and truly represent the actual color of the scene.

This contrast correction can also be used on gray-scale images when the contrast needs to be maintained and the image will be expanded from the dynamic range of the imager pixels (e.g. 12 bits) to a higher optical scene dynamic range, e.g. 16 bits. Thus, the output of contrast

corrector 205 can have, for example, a 16-bit dynamic range, even though each pixel of imager 201 has only 12-bit resolution.

Histogram equalizer/projection block 207, in one embodiment, is used to optimally display the wide dynamic range of the received input image (e.g., 12-bit image from imager 201 via line 216 and MUX 210 or 16-bit contrast-corrected image via contrast corrector 205 and MUX 210) onto a lower dynamic range monitor, such as 8-bit resolution output monitor 220. This serves to effectively display the maximum amount of information on output monitor 220 by maximizing the information content in each link in the video chain.

As will be appreciated, histogram equalization and histogram projection are commonly used methods of contrast enhancement using so-called "point processing" techniques. Using such techniques, an image with a uniform density of gray levels is produced generally maximizing the viewing contrast to present the most information to the viewer. Such techniques also map higher resolution data to a smaller resolution monitor without clipping, for optimal display on a monitor of limited resolution. Thus, the histogram equalization of histogram equalizer/projection block 207 will redistribute the gray scales so that the fine detail in both the bright and dark regions of the scene are properly enhanced. To perform such processing, histogram equalizer/projection block 207 requires only the histogram that is already available from the feedback function generator 206.

Line 216 allows the contrast correction of contrast corrector 205 to be bypassed if desired by setting multiplexer 211 to pass the uncorrected video on line 216 to output monitor 220. Line 217 allows the histogram equalization and projection of histogram equalizer/projection block 207 to be bypassed if desired by setting multiplexer 211 to pass the uncorrected video on line 217 to output monitor 220. Thus, by appropriately switching MUXs 210 and 211, one of four video signals may be displayed on output monitor 220: (1) unprocessed (i.e. skipping contrast corrector 205 and histogram equalizer/projection block 207); (2) contrast enhanced (i.e. skipping histogram equalizer/projection block 207); (3) histogram enhanced (i.e. skipping contrast corrector 205); or (4) histogram and contrast enhanced.

As will be appreciated, the dynamic feedback of the present invention may be used with charge capacity control voltage functions other than the two-voltage non-linear function illustrated in Figs. 1B and 1C. For example, multiple discrete steps and voltages, or a continuously increasing charge capacity control voltage may be used, as may linearly increasing

charge capacity control voltage waveforms. In these cases, global brightness distribution information provided by histogrammer 204 is used to suitably adjust these functions. Thus, for example, if a continuously increasing charge capacity control voltage is used, the brightness of the brightest object in the previous frame is used to adjust the shape of the charge capacity control voltage function so that light levels of this brightness will just saturate. In this case, feedback function generator 206 generates function information that instructs imager 201 how to vary the charge capacity control voltage function.

It will also be appreciated that histograms from previous frames other than the immediately previous frame may be used. For example, a histogram of a running average of the last five frames may be used.

It will be understood that various changes in the details, materials, and arrangements of the parts which have been described and illustrated above in order to explain the nature of this invention may be made by those skilled in the art without departing from the principle and scope of the invention as recited in the following claims.

**CLAIMS**

What is claimed is:

1. A imaging system, comprising:

5 (a) an imager having an array of photodetectors, each of which accumulates charge during an integration period as a result of light detected during said integration period, said array having a charge capacity which increases during the integration period; and

10 (b) a charge capacity controller coupled to said imager which adjusts how the imager increases the charge capacity of the array based upon the brightness distribution detected by said imager during at least one previous integration period.

2. The imaging system of claim 1, wherein:

15 the imager provides a video frame after the integration period in accordance with the charge accumulated by each photodetector;

the imager increases the charge capacity of the array during the integration period in accordance with a function and function information that specifies how to vary the function;

20 the charge capacity controller comprises a function generator which generates the function information in accordance with the brightness distribution of at least one previous video frame provided by the imager.

3. The imaging system of claim 2, wherein the charge capacity controller further comprises a histogrammer coupled to the imager and to the function generator, wherein the  
25 histogrammer receives video frames provided by the imager and provides a histogram containing the brightness distribution to the function generator.

4. The imaging system of claim 3, wherein the charge capacity controller further comprises a histogram equalization/projection block coupled to the histogrammer and to the  
30 imager, wherein the histogram equalization/projection block uses the histogram for a current video frame to optimally display the informational content of the video frame on a monitor.

5. The imaging system of claim 2, wherein the charge capacity controller further comprises a contrast corrector, wherein:

the function generator generates inverse function information; and

the contrast corrector receives video frames provided by the imager, receives the inverse  
5 function information provided by the function generator, and uses the inverse function information to remove the effect in video frames caused by the charge capacity of the array of photodetectors being increased during the integration period.

10 6. The imaging system of claim 2, wherein the imager increases the charge capacity of the array of photodetectors during the integration period by applying a first charge capacity control voltage to the array of photodetectors during a first portion of the integration period and a second charge capacity control voltage to the array of photodetectors after the first portion, wherein the length of the first portion is determined in accordance with the function information  
15 provided by the function generator and the second charge capacity control voltage is greater than the first charge capacity control voltage.

7. The imaging system of claim 2, wherein:

the function generator generates the function information in accordance with the  
20 brightness distribution of the most recent previous video frame provided by the imager; and

the function information is generated by the function generator so that light having a brightness level of the brightest object in the most recent previous video frame and impinging upon a photodetector of the imager during the integration period  
25 will not cause charge to accumulate in excess of the charge capacity of the photodetector at the end of the integration period.

8. The imaging system of claim 7, wherein the function information is generated by the function generator so that the light will cause charge to accumulate that just reaches but does not  
30 exceed the charge capacity of the photodetector at the end of the integration period.

9. The imaging system of claim 1, wherein the imager is a complementary metal-oxide

semiconductor imager having an array of virtual gate buried n-channel photodetectors, wherein each photodetector has a charge capacity related to the magnitude of a charge capacity control voltage applied to the photodetector.

5           10. The imaging system of claim 1, wherein the imager comprises an array charge-coupled device (CCD) photodetectors, wherein each CCD photodetector has a charge capacity related to the magnitude of a charge capacity control voltage applied to the CCD photodetector.

10           11. An imaging system, comprising a charge capacity controller coupled to an imager having an array of photodetectors, each of which accumulates charge during an integration period as a result of light detected during said integration period, said array having a charge capacity which increases during the integration period, wherein the charge capacity controller adjusts how the imager increases the charge capacity of the array based upon the brightness distribution detected by said imager during at least one previous integration period.

15




12. A method, comprising the steps of:

- (a) increasing the charge capacity of an array of photodetectors of an imager during an integration period during which each photodetector accumulates charge as a result of light detected during said integration period; and
- 20           (b) adjusting how the charge capacity of the array is increased based upon the brightness distribution detected by the imager during at least one previous integration period.


13. An imaging system, comprising:

- (a) means for increasing the charge capacity of an array of photodetectors of an imager
- 25           during an integration period during which each photodetector accumulates charge as a result of light detected during said integration period; and
- (b) means for adjusting how the charge capacity of the array is increased based upon the brightness distribution detected by the imager during at least one previous integration period.


30

$1/2$ **FIG. 1A****FIG. 1B****FIG. 1C**

2/2



**FIG. 2**



300

**FIG. 3**

## INTERNATIONAL SEARCH REPORT

International application No.  
PCT/US98/11106

## A. CLASSIFICATION OF SUBJECT MATTER

IPC(6) :G11C 19/28; H01J 31/49; G06K 7/00, 9/00

US CL :377/58; 250/330; 382/312, 100, 145

According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 377/58; 250/330 ; 382/312, 100, 145

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched  
NONEElectronic data base consulted during the international search (name of data base and, where practicable, search terms used)  
APS

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	US 3,953,733 A (LEVINE) 27 APRIL 1976, COL. 2, LINES 27-35; COL. 4, LINES 40-60; FIG. 1.	1-13
Y	US 4,523,326 A (HEWITT ET AL.) 11 JUNE 1985, FIG. 1; COL. 5, LINES 24-27; COL. 10, LINES 54-56; COL. 16, LINES 27-31; COL. 3, LINES 50-67.	1-13



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:	*T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
*A* document defining the general state of the art which is not considered to be of particular relevance	*X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
*B* earlier document published on or after the international filing date	*Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
*L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	*A* document member of the same patent family
*O* document referring to an oral disclosure, use, exhibition or other means	
*P* document published prior to the international filing date but later than the priority date claimed	

Date of the actual completion of the international search

28 SEPTEMBER 1998

Date of mailing of the international search report

05 NOV 1998

Name and mailing address of the ISA/US  
Commissioner of Patents and Trademarks  
Box PCT  
Washington, D.C. 20231

Facsimile No. (703) 305-3230

Authorized officer

JOSE COUSO

Telephone No. (703) 305-4774